



door-coupling rotary operating mechanism for circuit breaker size S00/S0 handle gray new design !!! phased-out product !!! replacement type is 3RV2926-3B

| General technical data | | |
|-------------------------------------|-----|--|
| product brand name | | SIRIUS |
| product designation | | door-coupling rotary operating mechanism for heavy-duty operating conditions |
| size of the circuit-breaker | | S0 |
| design of the product | | standard |
| suitability for use | | circuit-breakers S0 |
| ambient temperature | | |
| • during storage | °C | -50 ... +80 |
| • during operation | °C | -20 ... +70 |
| operating frequency maximum | 1/h | 15 |
| color of the actuating element | | gray |
| Installation/ mounting/ dimensions | | |
| mounting position | | any |
| fastening method | | screw fixing |
| width | mm | 75 |
| height | mm | 75 |
| depth | mm | 78 |
| length | mm | 300 |
| diameter | mm | 40 |
| required spacing for grounded parts | | |
| • forwards | mm | 0 |
| • backwards | mm | 0 |
| • upwards | mm | 0 |
| • at the side | mm | 0 |
| • downwards | mm | 0 |
| Certificates/ approvals | | |
| certificate of suitability | | CE / UL / CSA |
| General Product Approval | | Test Certificates Marine / Shipping |



[Confirmation](#)



[Type Test Certificates/Test Report](#)



Marine / Shipping other



[Confirmation](#)



Further information

Information- and Downloadcenter (Catalogs, Brochures,...)

<https://www.siemens.com/ic10>

Industry Mall (Online ordering system)

<https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3RV2926-2B>

Cax online generator

<http://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3RV2926-2B>

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

<https://support.industry.siemens.com/cs/ww/en/ps/3RV2926-2B>

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...)

http://www.automation.siemens.com/bilddb/cax_de.aspx?mlfb=3RV2926-2B&lang=en

last modified:

12/23/2020